

# The TRIUMPH Corporation

## SERVICE BULLETIN

BULLETIN NO. 5

1963 and 1964 "B" RANGE 650cc TWIN MODELS

January 17, 1964

This chart shows wire code colors and connections at the separate lighting and ignition switches. This information applies ONLY to 1963 and 1964 650cc Twin models with 6 Volt lighting systems and twin contact breaker points and dual coil ignition. This does not apply to the 1964 Thunderbird (6T) model which has 12 Volt system.

<u>Light Switch Terminal Numbers</u>	<u>Color Code</u>	<u>Wires Connect to:</u>
1	Red with Black tracer	Parking Lamp
2	Brown with White tracer	Ammeter Positive Terminal
3	Blue	Headlamp Dipper Switch
4	White with Green tracer	Alternator Junction Block White/Green
5	Black	Ignition Switch #18 Terminal
6	Not Used	
7	Green with Black tracer	Rectifier Top Terminal
8	Brown with Green tracer	Tail Lamp
10	Brown with White tracer	Rectifier Middle Terminal
11	Brown with Green tracer	Speedometer & Tachometer lights
<u>Ignition Switch Terminal Numbers</u>		
12	Not Used	
12A	Brown with White tracer	Rectifier Middle Terminal
13	White	Ignition Coils - Negative Terminals
13A	Not Used	
14	Not Used	
15	Black with White tracer	LEFT HAND Ignition Coil Positive Terminal
16	Green with Yellow tracer	Alternator Junction Block Gr/Yellow
17	Not Used	
18	Black	Lighting Switch #5 Terminal
19	Not Used	